








- DIN Rail installation
- Advanced pre-setting one week before
- Lithium battery power reserve when electric supply is cut off
- Voltage rating: AC220V 50/60HZ
- Voltage limit: AC180V ~ 250V
- Hysteresis: ≤ 2 sec/day (25°C)
- ON/OFF operation: 16 ON and 16 OFF programmable slots
- Power consumption: 7.5VA(max)
- Display: LCD
- Load capacity:
 - Resistive load: 20A/250VAC
 - Lagging load: 12A
 - Lamp load: 2500W
- Ambient temperature: -10~+40°C
- Ambient humidity: 35~85%RH


SETTING TIME

- Hold down  and press D+ to select the current day
- Hold down  and press H+ to select hours
- Hold down  and press M+ to select minutes

SETTING AUTO "ON" AND "OFF" TIME

(The time has 16 programmable "on" and "off" slots)

- Press , you will enter Slot 1 "on"
- Press D+, to select which day of the week to switch on
- Press H+ to set on time
- Press M+ to set on time
- Press , to enter Slot 1 "off"
- Press D+, to select which day of the week to switch off
- Press H+ to set off time
- Press M+ to set off time

(If the rest of the slots are not needed, continue pressing  to exit the rest of the slots. If extra slots are needed, repeat the above steps)

SELECTING MODE

MANUAL MODE:

- Press "MANUAL" to "ON" to manually switch the timer on
- Press "MANUAL" to "OFF" to manually switch the timer off

AUTO MODE:

- Make sure to leave the timer in "ON AUTO" if the timer is meant to be "ON" based on your set programmed time.
- Leave the time in "OFF AUTO" if the timer is meant to be "OFF" based on your set programmed time.

RESET SETTING

- Press "RESET" to reset timer